



Reconnect a camera to a wireless network if the router, equipment, or Wi-Fi settings change

If a customer gets a new router or changes their Wi-Fi credentials (i.e., network name or password), they need to reconfigure the video device locally to connect to the new network. There are multiple methods available to restore communication without the need to delete or factory reset an enrolled video device.

Important: When the video device is disconnected from the internet, it must be reconnected locally. Remote commands will not reach the video device.



Reconnect the video device

To reconnect a video device to a Wi-Fi network using WPS mode: ^

This method applies to all WPS-enabled Alarm.com video devices.

Find the WPS button on the video device and router

Note: WPS is not available on all routers. Refer to the router's installation manual for additional instructions.

1. Locate the WPS button on the router. Typically, there is a button labeled *WPS*, , or .
2. Locate the WPS button on the video device. On most video device models, the button is labeled *WPS* or *Reset*.

Put the video device and router into WPS pairing mode

1. Hold the WPS button for about 2 to 3 seconds (or until the LED begins to flash blue) to put the video device into

WPS mode.

2. Press the WPS button on the router for 1 to 6 seconds to put the router into WPS mode. The time can vary significantly between router models. Typically, a light flashes on the router to indicate it is in WPS mode. If there is no LED or a blinking red LED, WPS might be disabled on the router.

Wait for the video device to connect

1. Wait approximately 2 minutes for the video device to connect to the router.
2. The video device is connected when the status LED stays solid green.

To reconnect a video device to a Wi-Fi network using Access Point (AP) Mode: ^

Connect a Wi-Fi capable device to the video device's AP network

1. Press and hold the WPS/Reset button on the back of the video device for 5 to 7 seconds until the LED starts flashing white.
2. Using a computer, smartphone, or tablet, connect to the Wi-Fi network named *ALARM (##.##.##)*. The numbers in parentheses are the last six digits of the video device's MAC address.

Configure the video device's Wi-Fi network using the AP mode user interface

1. Using a web browser on the Wi-Fi capable device, enter **192.168.1.1** in the web browser and press **Enter**.
2. Follow the on-screen instructions to connect the video device to the customer's wireless network.
3. Click **Scan for wireless networks**.
4. Click the name of the customer's Wi-Fi network.
5. In the *Security Key* field, enter the customer's Wi-Fi password.
6. Click **Ok** in the pop-up window that appears asking to refer to the website.

Wait for the video device to connect

- Wait for the LED to turn solid green, and then try to view live video on the Customer Website or app. If the video device's LED does not turn solid green, reboot the video device and retry this procedure.

To reconnect a video device to a Wi-Fi network using an Ethernet cable: ^

Connect the video device to the router using an Ethernet cable





1. Disconnect power from the video device.
2. Find an Ethernet/Cat5 cable that reaches from the video device to the router. This may require taking the video device down from its mounting location and bringing it to the router temporarily.
3. Plug one end of the Ethernet cable into the video device and the other end into the router. Typically, the router has LAN ports that are numbered one through four. Any of these ports should work.
4. Reconnect power to the video device, and wait for the video device's status LED to turn solid green. Once the video device's LED turns solid green, the new wireless information is ready to be programmed.

Configure the video device's wireless network settings

Power down the video device and disconnect the Ethernet cable

1. Disconnect power from the video device.
2. Remove the Ethernet cable from the video device and router.
3. Reconnect power to the video device, and wait for the video device's status LED to turn solid green.

LED troubleshooting

LED pattern	Function	Troubleshooting
<p>Solid green</p> 	<p>The video device has an active internet connection.</p>	<ul style="list-style-type: none">• If the user is unable to view live video, disconnect the video device from power then reconnect it. Wait for the LED to turn solid green, and test again.
<p>Blinking green</p> 	<p>The video device has a local network connection only.</p>	<ol style="list-style-type: none">1. If the LED is flashing green for more than two minutes, power the video device down for a few seconds then apply power.2. Allow the video device to boot up. If the LED is still flashing green after a few minutes, remove power from the router for at least one minute, and restore power.3. Wait a few minutes for the internet connection to be re-established.
<p>Blinking red and green</p> 	<p>The password entered during Wi-Fi configuration may be incorrect.</p>	<ul style="list-style-type: none">• Repeat steps for To reconnect a camera to a Wi-Fi network using an Ethernet cable and enter the wireless information again. <p>Note: This LED pattern is shared with the factory reset pattern.</p>
<p>Solid red</p> 	<p>The video device is unable to connect to a wireless network.</p>	<ol style="list-style-type: none">1. The connection typically fails if the router and video device are too far from each other for a strong wireless connection.2. Move the video device and router closer together.3. If another attempt is unsuccessful, try another method of reconnecting the video device to a wireless network (i.e., Ethernet or AP mode).