

## 6150RF

### Fixed Language Integrated Keypad/Transceiver

Add wireless technology to any installation with Honeywell's 6150RF keypad. It offers the unbeatable combination of attractive, convenient features and competitive value in a single, quick-install package. The integrated design solves even the trickiest installation challenges and reduces costs by letting you add full wireless capability to any compatible VISTA™ control—without additional wiring or sacrificing zones.

Dealers can add the 5828 and 5828V wireless keypads to VISTA for the first time, presenting a tremendous upsell opportunity by letting them offer their customers secondary wireless keypads on every installation with virtually no install time.



With Door Attached



Without Door

## FEATURES

- 6150 Fixed Language Keypad
- Built-in 16-Zone wireless transceiver
- Compatible with 5828 and 5828V wireless keypads
- Single four-wire run is all that's required
- It is the ideal choice where wireless keys are to be used:
  - Keys can be programmed at the panel, just as they would with the 5881ENM\*
  - Keys can be enrolled locally at the keypad, without taking up additional zones at the control
- Fully compatible with all 5800 wireless devices including bidirectional
- On-board single relay provides a low cost solution for opening garage doors.

### STYLISHLY DESIGNED

- Sleek white design blends with any décor
- Contoured, removable door lets customers customize the keypad for the look they want
- With the door closed the keypad has a smooth, unobtrusive appearance

### EASY TO OPERATE

- The Fixed Language display is easy to read, with large characters and simplified descriptions
- The sounder beeps to help identify security system status
- Comfortable soft-touch keys labeled with simple commands are illuminated for nighttime visibility
- Four larger function keys can be programmed for one touch operation and are accessible even when the door is closed

\* 5881ENM is not available in Canada  
Wi-Fi® IEEE 802.11 B/G/N radio

# 6150RF

Fixed Language Integrated Keypad/Transceiver

## SPECIFICATIONS

---

### DIMENSIONS

- 4-7/8" H x 6" W x 1" D  
(125mm x 160mm x 25 mm)

### SOUNDER

- Piezo Electric

### WIRING

- - (Black): Ground
- + (Red): +12 VDC (Aux. Power)
- D1 (Green): "Data In" to control panel
- D0 (Yellow): "Data out" from control panel

### CURRENT

- Standby: 80ma
- Activated: 105ma

## ORDERING

|          |   |
|----------|---|
| 6150RF   | Fixed Language Keypad with Integrated Transceiver – English |
| 6150RFFR | Fixed Language Keypad with Integrated Transceiver – French  |
| 5828     | Wireless Fixed English Keypad                               |
| 5828V    | Wireless Fixed English Keypad with Voice                    |

### For more information

[www.honeywell.com/security](http://www.honeywell.com/security)

### Honeywell Security and Fire

2 Corporate Center Dr. Suite 100  
P.O. Box 9040  
Melville, NY 11747  
1.800.323.4576  
[www.honeywell.com](http://www.honeywell.com)

L/6150RFD/D | 12/16  
© 2016 Honeywell International Inc.

**Honeywell**